

SMA Sunny Island (empfohlene Einstellparameter)		
	Baureihe	OPzV solar.power OPzV bloc solar.power
1.	Am Sunny Remote Control in Expertenmodus wechseln	
2.	222.01 BatChrgCurMax	20A pro 100Ah (C10)
3.	222.02 AptTmBoost	120 min
	222.07 ChrgVtgBoost	2,40 V/Zelle
4.	222.03 AptTmFull	7 h
	222.05 CycTmFull	14 Tage
	222.08 ChrgVtgFull	2,50 V/Zelle
5.	222.04 AptTmEqu	10 h
	222.06 CycTmEqu	90 Tage
	222.09 ChrgVtgEqu	2,55 V/Zelle